



## Generator Guidelines – Community Trailer



### Step one

- Ensure there is enough unleaded fuel
- Check the gauge first
- Unscrew the fuel cap



### Step two

- Fill using the Jerry can located at the front box of the trailer and funnel
- Ensure you replace the fuel cap



### Step 3

- Turn the dial to 'ON'







### Step 4

- Ensure this switch is 'on'



### Step 5

- Pull out the choke to release fuel

	<p><b>Step 6</b></p> <ul style="list-style-type: none"> <li>- Pull the starter cord, quick and firmly</li> <li>- Ensure you hold the generator still whilst doing this with your other hand</li> </ul>
	<p><b>Step 7</b></p> <ul style="list-style-type: none"> <li>- Once running, push the choke in again</li> </ul>
	<p><b>Step 8</b></p> <ul style="list-style-type: none"> <li>- Connect equipment to be run off the generator</li> </ul>
	<p><b>Step 8</b></p> <ul style="list-style-type: none"> <li>- To turn off, move the dial to the 'OFF position'</li> <li>- Turn the red switch to 'OFF'</li> </ul>